

12V N-Channel NexFET™ Power MOSFETs

Check for Samples: [CSD13202Q2](#)

FEATURES


- Ultralow Q_g and Q_{gd}
- Low Thermal Resistance
- Avalanche Rated
- Pb Free Terminal Plating
- RoHS Compliant
- Halogen Free
- SON 2-mm × 2-mm Plastic Package

APPLICATIONS


- Optimized for Load Switch Applications
- Storage, Tablets, and Handheld Devices
- Optimized for Control FET Applications
- Point of Load Synchronous Buck Converters

DESCRIPTION

This 12V, 7.5mΩ NexFET™ power MOSFET has been designed to minimize losses in power conversion and load management applications. The SON 2 x 2 offers excellent thermal performance for the size of the package.



P0108-01



PRODUCT SUMMARY

V _{DS}	Drain to Source Voltage	12	V	
Q _g	Gate Charge Total (4.5V)	5.1	nC	
Q _{gd}	Gate Charge Gate to Drain	0.76	nC	
R _{DS(on)}	Drain to Source On Resistance	V _{GS} = 2.5V	9.1	mΩ
		V _{GS} = 4.5V	7.5	mΩ
V _{GS(th)}	Threshold Voltage	0.8	V	

ORDERING INFORMATION


Device	Package	Media	Qty	Ship
CSD13202Q2	SON 2-mm × 2-mm Plastic Package	7-Inch Reel	3000	Tape and Reel

ABSOLUTE MAXIMUM RATINGS

T _A = 25°C unless otherwise stated	VALUE	UNIT	
V _{DS}	Drain to Source Voltage	12	V
V _{GS}	Gate to Source Voltage	±8	V
I _D	Continuous Drain Current (Package Limit)	22	A
	Continuous Drain Current ⁽¹⁾	14.4	A
I _{DM}	Pulsed Drain Current, T _A = 25°C ⁽²⁾	76	A
P _D	Power Dissipation ⁽¹⁾	2.7	W
T _J , T _{STG}	Operating Junction and Storage Temperature Range	-55 to 150	°C
E _{AS}	Avalanche Energy, single pulse I _D = 20A, L = 0.1mH, R _G = 25Ω	20	mJ

(1) R_{θJA} = 45°C/W on 1in² Cu (2 oz.) on .060" thick FR4 PCB.

(2) Pulse duration 10μs, duty cycle ≤2%



Please be aware that an important notice concerning availability, standard warranty, and use in critical applications of Texas Instruments semiconductor products and disclaimers thereto appears at the end of this data sheet.

NexFET is a trademark of Texas Instruments.



These devices have limited built-in ESD protection. The leads should be shorted together or the device placed in conductive foam during storage or handling to prevent electrostatic damage to the MOS gates.

ELECTRICAL CHARACTERISTICS

$T_A = 25^\circ\text{C}$, unless otherwise specified


PARAMETER		TEST CONDITIONS	MIN	TYP	MAX	UNIT
Static Characteristics						
BV_{DSS}	Drain to Source Voltage	$V_{\text{GS}} = 0\text{V}$, $I_{\text{D}} = 250\mu\text{A}$	12			V
I_{DSS}	Drain to Source Leakage Current	$V_{\text{GS}} = 0\text{V}$, $V_{\text{DS}} = 9.6\text{V}$		1		μA
I_{GSS}	Gate to Source Leakage Current	$V_{\text{DS}} = 0\text{V}$, $V_{\text{GS}} = 8\text{V}$		100		nA
$V_{\text{GS}(\text{th})}$	Gate to Source Threshold Voltage	$V_{\text{DS}} = V_{\text{GS}}$, $I_{\text{DS}} = 250\mu\text{A}$	0.58	0.80	1.10	V
$R_{\text{DS}(\text{on})}$	Drain to Source On Resistance	$V_{\text{GS}} = 2.5\text{V}$, $I_{\text{DS}} = 5\text{A}$		9.1	11.6	$\text{m}\Omega$
		$V_{\text{GS}} = 3\text{V}$, $I_{\text{DS}} = 5\text{A}$		8.4	10.4	$\text{m}\Omega$
		$V_{\text{GS}} = 4.5\text{V}$, $I_{\text{DS}} = 5\text{A}$		7.5	9.3	$\text{m}\Omega$
g_{fs}	Transconductance	$V_{\text{DS}} = 6\text{V}$, $I_{\text{DS}} = 5\text{A}$		44		S
Dynamic Characteristics						
C_{ISS}	Input Capacitance	$V_{\text{GS}} = 0\text{V}$, $V_{\text{DS}} = 6\text{V}$, $f = 1\text{MHz}$	767	997		pF
C_{OSS}	Output Capacitance		506	657		pF
C_{RSS}	Reverse Transfer Capacitance		43	56		pF
R_g	Series Gate Resistance			0.7	1.4	Ω
Q_g	Gate Charge Total (4.5V)	$V_{\text{DS}} = 6\text{V}$, $I_{\text{DS}} = 5\text{A}$		5.1	6.6	nC
Q_{gd}	Gate Charge – Gate to Drain			0.76		nC
Q_{gs}	Gate Charge Gate to Source			0.98		nC
$Q_{\text{g}(\text{th})}$	Gate Charge at V_{th}			0.57		nC
Q_{OSS}	Output Charge			5.7		nC
$t_{\text{d}(\text{on})}$	Turn On Delay Time	$V_{\text{DS}} = 6\text{V}$, $V_{\text{GS}} = 4.5\text{V}$, $I_{\text{DS}} = 5\text{A}$ $R_g = 2\Omega$		4.5		ns
t_r	Rise Time			28		ns
$t_{\text{d}(\text{off})}$	Turn Off Delay Time			11.0		ns
t_f	Fall Time			13.6		ns
Diode Characteristics						
V_{SD}	Diode Forward Voltage	$I_{\text{DS}} = 5\text{A}$, $V_{\text{GS}} = 0\text{V}$	0.75	1		V
Q_{rr}	Reverse Recovery Charge	$V_{\text{DD}} = 6\text{V}$, $I_{\text{F}} = 5\text{A}$, $di/dt = 200\text{A}/\mu\text{s}$		13		nC
t_{rr}	Reverse Recovery Time			28		ns

THERMAL CHARACTERISTICS


($T_A = 25^\circ\text{C}$ unless otherwise stated)

PARAMETER		MIN	TYP	MAX	UNIT
$R_{\text{θJC}}$	Thermal Resistance Junction to Case ⁽¹⁾			6.4	$^\circ\text{C}/\text{W}$
$R_{\text{θJA}}$	Thermal Resistance Junction to Ambient ⁽¹⁾⁽²⁾			60	$^\circ\text{C}/\text{W}$

(1) $R_{\text{θJC}}$ is determined with the device mounted on a 1-inch² (6.45-cm²), 2-oz. (0.071-mm thick) Cu pad on a 1.5-inch × 1.5-inch (3.81-cm × 3.81-cm), 0.06-inch (1.52-mm) thick FR4 PCB. $R_{\text{θJC}}$ is specified by design, whereas $R_{\text{θJA}}$ is determined by the user's board design.
 (2) Device mounted on FR4 material with 1-inch² (6.45-cm²), 2-oz. (0.071-mm thick) Cu.



Max $R_{\theta JA}$ = 60 when mounted on 1 inch² (6.45 cm²) of 2-oz. (0.071-mm thick) Cu.



Max $R_{\theta JA}$ = 210 when mounted on minimum pad area of 2-oz. (0.071-mm thick) Cu.

TYPICAL MOSFET CHARACTERISTICS

(T_A = 25°C unless otherwise stated)




Figure 1. Transient Thermal Impedance




Figure 2. Saturation Characteristics




Figure 3. Transfer Characteristics

TYPICAL MOSFET CHARACTERISTICS (continued)

($T_A = 25^\circ\text{C}$ unless otherwise stated)




Figure 4. Gate Charge




Figure 5. Capacitance




Figure 6. Threshold Voltage vs. Temperature




Figure 7. On-State Resistance vs. Gate-to-Source Voltage




Figure 8. Normalized On-State Resistance vs. Temperature




Figure 9. Typical Diode Forward Voltage

TYPICAL MOSFET CHARACTERISTICS (continued)

($T_A = 25^\circ\text{C}$ unless otherwise stated)




Figure 10. Maximum Safe Operating Area




Figure 11. Single Pulse Unclamped Inductive Switching





Figure 12. Maximum Drain Current vs. Temperature

MECHANICAL DATA


Q2 Package Dimensions



M0165-01


DIM	MILLIMETERS			INCHES		
	MIN	NOM	MAX	MIN	NOM	MAX
A	0.700	0.750	0.800	0.028	0.030	0.032
A1	0.000		0.050	0.000		0.002
b	0.250	0.300	0.350	0.010	0.012	0.014
C	0.203 TYP			0.008 TYP		
D	2.000 TYP			0.080 TYP		
D1	0.900	0.950	1.000	0.036	0.038	0.040
D2	0.300 TYP			0.012 TYP		
E	2.000 TYP			0.080 TYP		
E1	0.900	1.000	1.100	0.036	0.040	0.044
E2	0.280 TYP			0.0112 TYP		
E3	0.470 TYP			0.0188 TYP		
e	0.650 BSC			0.026 TYP		
K	0.280 TYP			0.0112 TYP		
K1	0.350 TYP			0.014 TYP		
K2	0.200 TYP			0.008 TYP		
K3	0.200 TYP			0.008 TYP		
K4	0.470 TYP			0.0188 TYP		
L	0.200	0.25	0.300	0.008	0.010	0.012

Recommended PCB Pattern




For recommended circuit layout for PCB designs, see application note **SLPA005 – Reducing Ringing Through PCB Layout Techniques**.

Recommended Stencil Pattern



Note: All dimensions are in mm, unless otherwise specified.

Q2 Tape and Reel Information



M0168-01

Notes:

1. Measured from centerline of sprocket hole to centerline of pocket
2. Cumulative tolerance of 10 sprocket holes is ± 0.20
3. Other material available
4. Typical SR of form tape Max 10^9 OHM/SQ
5. All dimensions are in mm, unless otherwise specified.

PACKAGING INFORMATION

Orderable Device	Status (1)	Package Type	Package Drawing	Pins	Package Qty	Eco Plan (2)	Lead/Ball Finish (6)	MSL Peak Temp (3)	Op Temp (°C)	Device Marking (4/5)	Samples
CSD13202Q2	ACTIVE	SON	DQK	6	3000	Green (RoHS & no Sb/Br)	CU SN	Level-1-260C-UNLIM	-40 to 85		Samples

(1) The marketing status values are defined as follows:

ACTIVE: Product device recommended for new designs.

LIFEBUY: TI has announced that the device will be discontinued, and a lifetime-buy period is in effect.

NRND: Not recommended for new designs. Device is in production to support existing customers, but TI does not recommend using this part in a new design.

PREVIEW: Device has been announced but is not in production. Samples may or may not be available.

OBsolete: TI has discontinued the production of the device.

(2) Eco Plan - The planned eco-friendly classification: Pb-Free (RoHS), Pb-Free (RoHS Exempt), or Green (RoHS & no Sb/Br) - please check <http://www.ti.com/productcontent> for the latest availability information and additional product content details.

TBD: The Pb-Free/Green conversion plan has not been defined.

Pb-Free (RoHS): TI's terms "Lead-Free" or "Pb-Free" mean semiconductor products that are compatible with the current RoHS requirements for all 6 substances, including the requirement that lead not exceed 0.1% by weight in homogeneous materials. Where designed to be soldered at high temperatures, TI Pb-Free products are suitable for use in specified lead-free processes.

Pb-Free (RoHS Exempt): This component has a RoHS exemption for either 1) lead-based flip-chip solder bumps used between the die and package, or 2) lead-based die adhesive used between the die and leadframe. The component is otherwise considered Pb-Free (RoHS compatible) as defined above.

Green (RoHS & no Sb/Br): TI defines "Green" to mean Pb-Free (RoHS compatible), and free of Bromine (Br) and Antimony (Sb) based flame retardants (Br or Sb do not exceed 0.1% by weight in homogeneous material)

(3) MSL, Peak Temp. - The Moisture Sensitivity Level rating according to the JEDEC industry standard classifications, and peak solder temperature.

(4) There may be additional marking, which relates to the logo, the lot trace code information, or the environmental category on the device.

(5) Multiple Device Markings will be inside parentheses. Only one Device Marking contained in parentheses and separated by a "~" will appear on a device. If a line is indented then it is a continuation of the previous line and the two combined represent the entire Device Marking for that device.

(6) Lead/Ball Finish - Orderable Devices may have multiple material finish options. Finish options are separated by a vertical ruled line. Lead/Ball Finish values may wrap to two lines if the finish value exceeds the maximum column width.

Important Information and Disclaimer: The information provided on this page represents TI's knowledge and belief as of the date that it is provided. TI bases its knowledge and belief on information provided by third parties, and makes no representation or warranty as to the accuracy of such information. Efforts are underway to better integrate information from third parties. TI has taken and continues to take reasonable steps to provide representative and accurate information but may not have conducted destructive testing or chemical analysis on incoming materials and chemicals. TI and TI suppliers consider certain information to be proprietary, and thus CAS numbers and other limited information may not be available for release.

In no event shall TI's liability arising out of such information exceed the total purchase price of the TI part(s) at issue in this document sold by TI to Customer on an annual basis.



www.ti.com

PACKAGE OPTION ADDENDUM

18-Oct-2013

IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, enhancements, improvements and other changes to its semiconductor products and services per JESD46, latest issue, and to discontinue any product or service per JESD48, latest issue. Buyers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All semiconductor products (also referred to herein as "components") are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its components to the specifications applicable at the time of sale, in accordance with the warranty in TI's terms and conditions of sale of semiconductor products. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by applicable law, testing of all parameters of each component is not necessarily performed.

TI assumes no liability for applications assistance or the design of Buyers' products. Buyers are responsible for their products and applications using TI components. To minimize the risks associated with Buyers' products and applications, Buyers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any patent right, copyright, mask work right, or other intellectual property right relating to any combination, machine, or process in which TI components or services are used. Information published by TI regarding third-party products or services does not constitute a license to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of significant portions of TI information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. TI is not responsible or liable for such altered documentation. Information of third parties may be subject to additional restrictions.

Resale of TI components or services with statements different from or beyond the parameters stated by TI for that component or service voids all express and any implied warranties for the associated TI component or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

Buyer acknowledges and agrees that it is solely responsible for compliance with all legal, regulatory and safety-related requirements concerning its products, and any use of TI components in its applications, notwithstanding any applications-related information or support that may be provided by TI. Buyer represents and agrees that it has all the necessary expertise to create and implement safeguards which anticipate dangerous consequences of failures, monitor failures and their consequences, lessen the likelihood of failures that might cause harm and take appropriate remedial actions. Buyer will fully indemnify TI and its representatives against any damages arising out of the use of any TI components in safety-critical applications.

In some cases, TI components may be promoted specifically to facilitate safety-related applications. With such components, TI's goal is to help enable customers to design and create their own end-product solutions that meet applicable functional safety standards and requirements. Nonetheless, such components are subject to these terms.

No TI components are authorized for use in FDA Class III (or similar life-critical medical equipment) unless authorized officers of the parties have executed a special agreement specifically governing such use.

Only those TI components which TI has specifically designated as military grade or "enhanced plastic" are designed and intended for use in military/aerospace applications or environments. Buyer acknowledges and agrees that any military or aerospace use of TI components which have **not** been so designated is solely at the Buyer's risk, and that Buyer is solely responsible for compliance with all legal and regulatory requirements in connection with such use.

TI has specifically designated certain components as meeting ISO/TS16949 requirements, mainly for automotive use. In any case of use of non-designated products, TI will not be responsible for any failure to meet ISO/TS16949.

Products	Applications
Audio	www.ti.com/audio
Amplifiers	amplifier.ti.com
Data Converters	dataconverter.ti.com
DLP® Products	www.dlp.com
DSP	dsp.ti.com
Clocks and Timers	www.ti.com/clocks
Interface	interface.ti.com
Logic	logic.ti.com
Power Mgmt	power.ti.com
Microcontrollers	microcontroller.ti.com
RFID	www.ti-rfid.com
OMAP Applications Processors	www.ti.com/omap
Wireless Connectivity	www.ti.com/wirelessconnectivity
	TI E2E Community
	e2e.ti.com